

PH METER

pH Meter

This bench-top pH meter is an ideal help in every laboratory for routine or R&D level measurement. This very handy instrument measures pH, mV and has 40- point data memory storage.



SPECIFICATIONS:

- 1) **pH range:** -2.00 to 19.999
- 2) **Resolution:** 0.001 pH
- 3) **Relative Accuracy:** +/- 0.002 pH
- 4) **Slope:** 3 points 80% to 120%,
5 points 90% to 105%
- 5) **Sensor:** Combination pH electrode
- 6) **Calibration:** Auto-calibration
& printout of calibration Report.
- 7) **Millivolt:** mV range 0 to +/- 1999.9 mV
- 8) **Resolution:** +/- 0.1 mV
- 9) **Relative accuracy:** +/- 0.2 mV
- 10) **Input:** 1 BNC, 1 Banana, 1 ATC - PT 100
- 11) **Input Impedance:** > 1012ohms
- 12) **Report format:**
 - (a) Report of selected pH & mV reading with temperature.
 - (b) Calibration report
 - (c) Data table & Graph (optional)
- 13) **Temperature:**
 - a) Temperature: 0 to 150C
 - b) Resolution: 0.1C
 - c) Relative Accuracy: 0.2C
 - d) Sensor: RTD PT 100
 - e) Temp. Compensation: Auto/Manual

FEATURES

- 1) **Advanced microcontroller based** user friendly state-of-the-art product design.
- 2) PICO pH Meter complies to **USP and DIN standards.**
- 3) User interactive software in dialogue mode for ease of operation with protection against invalid entries.
- 4) 20 x 2 line back lighted **LCD display.**
- 5) Simultaneous measurement of **pH, mV and temperature.**
- 6) Non- volatile memory storage of :
40 pH and 40 mV readings with temperature in pre-selected GLP or Non-GLP format.
- 7) **Password protection** for calibration data and stored Readings.
- 8) **Calibration data with date and time** stamp for authentication. Facility to view the calibration data.
- 9) Calibration reminder alarm.
- 10) Alphanumeric entries of sample name, identification number for authentication.
- 11) **ATC by Pt.100** temperature sensor. Range 0° to 150° C.
3 point (Isopotential) or 5 point (linear or segmented) calibration protocol.
- 12) **Built-in real time clock (RTC)** for time display and on report printout.
- 13) Factory entered CUSTOMER NAME on report printout for authentication.
- 14) Error indication helps the user to trace the problem.
- 15) **Audible beep indication** during valid key operation.